1029ZH

Send to: NANCHAHAL, NEHA
PIERCE LAW CENTER
2 WHITE ST
CONCORD, NH 03301-4176

Time of Request: Wednesday, August 01, 2007 11:58:25 EST
Client ID/Project Name:
Number of Lines: 292
Job Number: 1821:40503956

Research Information

Service: Terms and Connectors Search
Print Request: Current Document: 58
Source: Utility, Design and Plant Patents
Search Terms: inventor(robert /2 rines)

58 of 81 DOCUMENTS

UNITED STATES PATENT AND TRADEMARK OFFICE GRANTED PATENT

2571163

Link to Claims Section

October 16, 1951

Electric system

INVENTOR: RINES ROBERT H

APPL-NO: 648482 (02)

FILED-DATE: February 18, 1946

GRANTED-DATE: October 16, 1951

PRIORITY: May 5, 1948 - 19480025244, United States (US); February 18, 1946 - 19460648482, United States (US)

PUB-TYPE: October 16, 1951 - Utility Patent having no previously published pre-grant publication (A)

PUB-COUNTRY: United States (US)

US-MAIN-CL: 315#1

US-ADDL-CL: 315#3, 315#10, 348#162

CL: 315, 348

SUMMARY:

The present invention relates to electric systems, and more particularly to radio-receiving systems that, while having more general fields of usefulness, are especially adapted for use in television. The present application is filed in response to a requirement for division in application Serial No. 648,482, filed February 18, 1946.

An object of the invention is to provide a new and improved electronically-controlled radio-receiving system.

Another object is to provide a new and improved radio-receiving mosaic.

A further object is to provide a novel cathode--ray tube circuit and mosaic for receiving radio waves.

Other and further objects will be explained hereinafter and will be more particularly pointed out in the appended claims.

The invention will now be more fully explained in connection with the accompanying drawings, in which Pig. 1 is a diagrammatic view of circuits and apparatus arranged and constructed in accordance with a preferred embodiment thereof; Pig. 2 is a view of a modification; Pig. 3 is a diagram showing an airplane object from which radio waves are reflected and scattered to the receiving system of Pig. 1; and Pig. 4 is a view of a further modification.

An electromagnetic-wave generator 4 is shown exciting a dipole 2 to produce ultra-high-frequency pulsed-radio energy, say, of 3 or 1.5 centimeters wavelength. A continuous-wave or any other type of modulated-wave generator may be employed, but pulsed energy, at present, has the advantage of economical and easy high-power ultra-high-frequency generation.

The waves emitted by the dipole 2 may be directed by a reflector 3 upon a parabolic reflector 6. The parabolic reflector 6 is shown directing the waves toward an object, say, an airplane 8, from which they are reflected and scattered toward a receiving station.

At the receiving station, the radio waves thus reflected and scattered from the object 8 may be focused by an electromagnetic dielectric lens 5, such as polystyrene, upon a bank or array T comprising a plurality of normally ineffective radio-receiving pick-up unit antenna elements. The dielectric lens 5 may be replaced by any other type of well-known lens, mirror or other directive system for focusing the electromagnetic energy scattered and reflected from the object 8 on the bank or array 7 of pick-up elements.

The pick-up elements of the bank or array 7 are. shown arranged in the form of rows and columns, in the proximity of the focal plane of the lens 5. The first or uppermost row of the bank is illustrated as comprising the sections 10, 12, 14, 16, etc., shown as equally spaced horizontally. The second row from the top is shown comprising the sections 18, 20, 22, etc. The third or next-lower row is shown comprising the sections 24, 26, etc., and so on for the remaining rows of pick-up elements. Though only a small number of pick-up units is shown in each row, this is merely for illustrative purposes, in order not to confuse the disclosure. It will be understood that, in practice, a large number of pick-up units will be employed in each row, say, 180.

The sections 10, 18, 24, etc., are arranged in the first or right-hand column. The sections 12, 20, 26, etc., are disposed in the second column from the right. The sections 14, 22, etc., are disposed in the third column from the right, and so on. There may be as many columns as there are pick-up units in each row. Though each column is shown as comprising only a few pick-up units, this is again in order no t to complicate the drawings.

The pick-up units will, of course, all receive the reflected or scattered radio waves through the lens 5 simultaneously. There will be focused on each pick-up unit a radio-frequency voltage corresponding to the scattering from a corresponding view of the object 8. The pick-up elements will thus receive different field strengths of radio energy, corresponding to the amount of energy reflected or scattered from the various parts of the object 8 and converged upon the array 7 of pick-up elements by the lens 5. A radio-energy picture of the object 8, as will be presently explained, is thus recorded upon the array, specific elemental areas of which will correspond to sper-cific elemental areas of the object 8. By means of the present invention, this radio-energy picture may be converted into a visible picture 123. According to the preferred embodiment of the invention, the visible picture 123 is caused to appear upon the fluorescent viewing screen 106 of a display cathode-ray oscilloscope tube 90. Though the tube 90, and also the hereinafter-described cathode-ray oscilloscope-like member 89, are shown operating on the electrostatic principle, magnetic deflection or a combination of magnetic and electrostatic forces may be employed. The invention provides a means for producing upon the screen 106 images corresponding to the radio-frequency energy received by the pick-up elements.

Provision is made for first rendering the noriiialiy ineffective pick-up units 10, 12, !4, 16, etc., of the first row successively effective momentarily in the display circuits; for then rendering the pick-up units 18, 20, 22, etc., of the second row successively effective momentarily; for then rendering the pick-up units 24, 26, etc., of the third row successively effective momentarily; and so OH; The pick-up units are shown arranged in an insulating disc 9 at the screen end of the oscilloscope-like member 89, and the pick-up units may be constituted of eleetrets.

An electret is a permanently charged dielectric formed by rilling the gap between two electrodes, say, with molten resin, carnauba wax, or beeswax, and subjecting the electrodes to high Voltage. By allowing the wax to cool during the application of the high voltage, a solidified permanently charged electric dipole is produced, having permanent

piezo-electric properties such that the dimensions thereof vary in response to voltages and the dimensional variation, in turn, produces further voltage variations. Investigations in this field are described, for example, by A. Gemant in the Philosophical Magazine, S. 7. vol. 20, No. 136. Suppl. November, 1935, pages 929 to 952.

As described by W. G. Cady in Piezoelectricity, McGraw-Hill, page 235, mixtures of the resin or carnauba wax with other dielectric substances have produced long-lasting eleetrets. It will presently be explained that if these dielectric bases are combined in the same manner with radio-absorbing-and-rectifying materials, such as silicon or uranium oxide, the eleetrets can be particularly well adapted to the purposes of the present invention. One of the electrodes of the electret, further, may serve to enhance the response to radio energy if, it is, for example, tuned to the radio waves, if it is one-quarter of a wavelength long.

The pick-up units previously described may be such eleetrets. The first row of units is shown composed of charged dielectrics 10, 12, 14, 16, etc., provided with top electrodes 110, 112, 114, 116, etc., respectively, and a common strip 43. The second row of units similarly is shown comprised of charged dielectrics 18, 20, 22, etc., provided with top electrodes 118, 120, 122, etc. and a common strip 51 connected to the strip 43. Similarly, the third row is shown composed of charged dielectrics 24, 26, etc., with top electrodes 124, 126, etc., and a common terminal strip 57 connected to the other common strips 43 and 51. The strips 43, 51 and 57 are shown connected by a conductor 78 to a grounded impedance 58, in the input circuit of an amplifier 79.

The cathode-ray-oscilloscope-like member 89 is shown provided with a cathode 95, a control-grid electrode 93 and an anode 97. Electrons emitted from the cathode will become enabled, in response to proper stimulation of the grid 93, to pass by the grid 93 to the anode 97 of the member 89. The electrons will continue to travel in a stream from the anode 97, between a pair of vertically disposed deflector plates 99 and 101, of which the plate 99 is shown grounded, and between a pair of horizontally disposed deflector plates 103 and 105, of which the plate is shown grounded, to impinge finally on the disc 9 of the member 89. A horizontal-sweep-time base, applied, as hereinafter more fully explained, to the vertically disposed deflector plates 99 and 101, will cause the electron stream from the cathode to become deflected horizontally, and a verti-cal-sweep-time base, applied to the horizontally disposed deflector plates 103 and !05, will cause the electron stream to become deflected vertically. The rows of electret pick-up units may be positioned along the successive paths of the electron stream to enable the stream to impinge on them as it successively sweeps out the successive rows of the array 7.

If, accordingly, the lens 5 is caused to focus the radio-energy picture on the oscilloscope-like member 89, the bank of eleetrets will act to ab-. sorb the incident radio-frequency energy. The absorbed radio-frequency energy will alter the initial permanent polarizing static charge or voltage with which the eleetrets become sensitized during their preparation. This alteration results from several factors, including heating or pyro-electric effects, the negative temperature coefficients of resistance and the piezo-electric properties of the eleetrets. Silicon and uraniumoxide detectors are known to absorb radio-frequency energy and to exhibit negative temperature coefficients of resistance.

The energy absorbed by each electret is a measure, of the intensity of the radio-frequency energy impinged thereon.

Across the electrodes of each electret, moreover, the radio-frequency energy will become rectified to produce direct-current potential differences. These potential differences are representative of the radio-frequency energy impressed on the top tuned electrodes of the eleetrets in the radio-receiving circuits comprising these tuned electrodes, the detecting eleetrets and the grounded conductor 78. The rectification is produced by :i"& gt; the detecting dielectric disposed between the electret electrodes. The variation of potential and charge along the bank of eleetrets is thus a measure of the radio-frequency energy impinged on the array by the lens 5.

The resistance of the silicon or uranium oxide, as well as of the wax of the electret, since their temperature coefficients are negative, changes with the intensity of the impinging radio-fre quency energy. A resistance variation is thus produced along the bank of eleetrets that is representative of the radio-frequency energy received by the respective eleetrets.

These three effects involving the change of the electret charge upon the absorption by the electrets of the radio-frequency energy, the production of the direct-current potentials as a result of the detection or rectification in the above-mentioned radio-receiving circuits, and the resistance changes render the electrets extremely sensitive. A radio-energy image of the object 8 becomes thus recorded upon the array of electrets as charged, potential and resistance distribution. The bank of electrets may be scanned according to either of two principles or according to a combination of the same. One principle involves measuring the variation in the electric charge and potential of the bank at the moment that the electron stream impinges Upon the successively disposed electrets to short-circuit them. The other principle involves measuring in a grounded preferably linear amplifier 79 the current along the electron stream as it impinges upon areas of different potential of the variously resistive electrets, completing the circuit to the ground through the successive electrets by way of the conductor 78.

Each electret will absorb and rectify the radio-frequency energy. Dependent upon the magnitude of this energy,will change the resistance and the charge of the electret. This change will result both as a consequence of the absorption and of the rectifying action by the electrets of the radio-frequency energy received by the electret electrodes. As the electron stream successively impinges upon the successively disposed electrets, during the scanning, it successively discharges them. This produces a corresponding change in the input voltage to the amplifier 79, indicative of the radio-frequency energy impinged on the respective electrodes.

The electron stream will instantaneously discharge each differently-charged and differently-potentialed electret to give an indication in the load 58 and the amplifier 79, or it will give rise to a change in the electron-beam current when it impinges upon the variously resistive electret elements, or there may be a combination of these effects.

The scanning of the electrets may obviously also operate on the principle of change in electron-beam current transmitted to the load 58 upon impinging on surfaces of various resistances. As the stream hits these electrets of different resistances, a change in beam current occurs, which manifests itself in the input circuit of the amplifier 79.

Mosaics of electrets for the member 89 may also take the form of Fig. 2, where electrets 81, 84, 86, 88 are provided with front electrodes 181, 184, 186, 188 exposed to the radio energy converged by the lens 5. The electrode strips 181, 184, 186, 188 may be of length one-quarter of the wave-length of the radio waves and may be in the interior of the tube 89, facing the electron stream, and may be scanned by it. The electrodes 281, 284, 286, 288 will be capacitively coupled to the front electrodes and will assume the homocharge of the electret. Thus, the electron stream will impinge on surfaces of different charge or potential, and the scanning will take place according to the principles previously described.

The electrets may be separated from adjacent electrets by dielectric material 200.

As the electron stream produced from the cathode 95, in response to appropriate horizon-tal-sweep-time-base voltages applied to the vertically disposed deflector plates 99 and 101 of the cathode-ray-tube-like member 89, travels across the pick-up elements in the disc 9, they will successively discharge into a grounded preferably linear amplifier 79, by way of a conductor 78. If desired, the amplifier 79 may be replaced by a bank of linear amplifiers, one corresponding to each of the pick-up elements.

The output of the amplifier 79 will obviously vary, at successive instants, in accordance with the radio-frequency energy received by the successive corresponding pick-up elements.

A pulse generator, which may, if desired, be the same pulse generator 4, may be employed to trigger a horizontal-time-base-sweep circuit 63 and a vertical-sweep circuit 69, according to conventional and well-known television technique. The pulse generator 4 may feed, through an at-.tenuator and rectifier 1, to an oscillator or any similar or equivalent television circuit. One such circuit is shown as a pulse-recurrence-frequency multiplier 65, for applying many pulses corresponding to each radio-frequency pulse for the period between successive radio-pulses, to trigger the horizontal-sweep circuit 63. The horizontal--time-base sweep will thereby be produced between the

vertically disposed deflector plates 99 and 101, occurring as many times, say, between successive radio-frequency trarismiss ioiisV &s there are rows of pick-up antennas. The pulse generator 4 may also feed, through the attenuator and rectifier I, to trigger the verticalsweep circuit 69, once corresponding to every radio-frequency transmission. One vertical sweep will then occur between the horizontally disposed plates 103, during the periods between successive radio pulse transmissions, corresponding to as many horizontal sweeps as there are rows of antennas, causing each of the horizontal sweeps to appear at successively lower levels on the oscilloscope-sweep face. If the circuit comprises an oscillator, the oscillations may be employed to trigger the horizontal sweep. The period of the oscillations which, as previously explained, is much less than the duration of each radio pulse, corresponds to the time of sweep across one row of the pick-up units in the disc 9.

If, as previously mentioned, continuous-wave radio transmission is employed, the vertical-sweep circuit 69 may be triggered to produce one vertical sweep corresponding to as many horizontal sweeps from the horizontal-sweep circuit 63 as there are rows of pick-up units.

Means is provided for producing upon the screen 106 of the display oscilloscope 90, images corresponding to the radio-frequency energy received by the corresponding pick-up mosaic antenna elements. The screen 106 is illuminated by an electron stream in the oscilloscope 90. This electron stream is synchronized to travel with the electron stream of the cathode-ray-like member 89. The horizontal-sweep circuit 63 is connected to the horizontal-deflector plate of the oscilloscope by a conductor 67, and to the horizontal-deflector plate 101 of the oscilloscope-like member 89 by the conductor 67 10 and a conductor 134. The vertical-sweep circuit 69 is connected to the vertical-deflector plate 102 of the oscilloscope by a conductor 71, and to the vertical-deflector plate 103 of the oscilloscope-like member 89 by the conductor 71 and a conductor 146.

The amplifier 79 is connected, by conductors; and 87, to the control-grid electrode 92 and the cathode 94 of the oscilloscope 90. The mosaic; of electrets becomes thus successively connected,, through the amplifier 79, to the control electrode. 92. Electrons emitted from the cathode 94 will! become enabled, in response to the action of thes amplifier 79, to pass by the grid 92, to the anode& gt; 96 of the oscilloscope tube 90. The electrons will!

continue to travel in a stream from the anode 9)6, between the pair of vertically disposed oscilloscope deflector plates 98 and 100, of which the plate 98 is shown grounded, and between the pair of horizontally disposed oscilloscope deflector plates 102 and 104, of which the plate 104 is shown grounded, to impinge finally on the fluorescent viewing screen 106 of the oscilloscope 90.

After each simultaneous horizontal sweep of 05 both the oscilloscope 90, and the oscilloscope-like member 89 has been completed, a successively larger voltage will be applied to the horizontally disposed deflector plates 102, (04, and 103, 105, respectively, by the vertical-sweep circuit. After the last such horizontal sweep, the voltage between the horizontally disposed plates 102, 104 and 103, will become restored to zero. The next horizontal sweep, therefore, will start again at the first or top row.

Successively disposed areas of the screen 106 of the oscilloscope will therefore correspond :to the similarly disposed mosaic-antenna sections in the disc 9 of the member 89. Each spot along a particular horizontal sweep, therefore, will become brightened on the screen 106 according to 5 the amount of radio energy received by the corresponding pick-up element, and fed, by way of the amplifier 79, to the control electrode 92, of the cathode-ray oscilloscope 90.

A more sensitive video signal device might be JQ any well-known bridge detector of, say, the Wheatstone construction. If the electrets are connected in a direct-current series circuit, then the bank of condenser electrets may serve as an extremely sensitive radio-detecting element of a Wheatstone bridge, in which they may be balanced against fixed impedance elements 212, 214 and 2-16, as shown in Fig. 4. The short-circuiting or exploring of each successive electret by the electron stream, diagrammatically shown as shorting switches 205, 207, 209, in parallel with the electrets 204, 203, 208, would thus be markedly indicated in the amplifier 79 and fed to the control electrode 92 of the display

oscilloscope SO.

Although the invention has been described in connection with mosaic-antennas arranged in rows and columns, it will be understood that this is not essential, for other arrangements are also possible. Antennas arranged along concentric circles covering the field, or a continuous spiral, will also serve, though the oscilloscope arrangement would, of course, be correspondingly modified.

In the case of the concentric circles and the spiral, the antennas would be rendered effective in two-dimensional order, as in the case of the rows and columns before described. The antennas disposed along one of the circles, for example, would first be rendered effective, then those along the next circle, and so on.

Further modifications will occur to persons skilled in the art, and all such are considered to fall within the spirit and scope of the invention, as defined in the appended claims.

ENGLISH-CLAIMS:
Return to Top of Patent

What is claimed is:

1. An electric system having, in combination, a plurality of permanently charged electrets, means for producing an electron stream for impinging on the plurality of electrets, and means for causing the electron stream to scan the plurality of electrets.

2. An electric system having, in combination, an oscilloscope-like member having a mosaic of permanently charged electrets for absorbing radio waves, means for producing an electron stream for impinging on the mosaic, and means for causing said stream to scan the mosaic.

3. An electric system having, in combination, radio-detecting means comprising a rectifying element sensitized with a permanent charge, and means for producing an electron stream for impinging on the radio-detecting means.

4. An electric system having, in combination, radio-detecting means comprising an element that rectifies radio energy applied thereto to produce direct-current voltage and the dimensions of which vary piezoelectrically in response to variations in the direct-current voltage produced by the element from the applied radio energy, the dimensional variations of the element producing, in turn, further variations in the direct-current voltage, and means for producing an electron stream for impinging upon the radio-detecting means. .. , . l 5. An electric system having, in combination ra plurality of sets of permanently charged electrets, the electrets of each set being connected together to a common terminal, a load, and means for connecting the common terminals to the load.

6. An electric system having, in combination, a plurality of sets of normally ineffective permanently charged electrets, the electrets of each set being connected together to a common terminal, a load, means for connecting the common terminals to the load, and means for render-ing the electrets of successive sets successively effective.

7. An electric system having, in combination, permanently charged electret means, and means for producing an electron stream for impinging on the electret means.

8. In combination with a plurality of permanently charged electrets, a plurality of elements corresponding, respectively, to the plurality of electrets and capacitively coupled thereto.

9. A mosaic having an insulating support, and a plurality of permanently charged electrets supported by the support.

10. An electron tube having a screen, and a mosaic of permanently charged electrets supported by the screen.

11. A plurality of radio-detecting elements each comprising a rectifying medium sensitized with a permanent

charge, alternately disposed with a plurality of elements having no initial charge.

12. A plurality of radio-detecting elements each comprising a rectifying medium sensitized with an initial voltage and disposed alternately with a plurality of elements having no initial voltage.

13. In combination with a mosaic of radio-receiving elements each having radio-wave receiving antenna means tuned to the frequency of the radio waves and absorbing means responsive to the radio waves received by the antenna means for absorbing the radio waves received thereby, a mosaic having insulated elements corresponding, respectively, to the first-named elements and capacitively coupled thereto.

14. An electric system having, in combination, a mosaic of radio-receiving elements each having radio-wave receiving antenna means tuned to the frequency of the radio waves and absorbing means responsive to the radio waves received by the antenna means for absorbing the radio waves received thereby, a mosaic having elements corr responding, respectively, to the first-named elements and capacitively coupled thereto, means for producing an electron stream impinging on one of the mosaics, and means for causing the stream to scan the said one mosaic.

15. In combination with a mosaic of radio-receiving elements each having radio-wave receiving antenna means tuned to the frequency of the radio waves and rectifying means responsive to the radio waves received by the antenna means for absorbing and rectifying the received radio waves, a mosaic having elements corresponding, respectively, to the first-named elements and car pacitively coupled thereto.

16. An: electron tube having a screen, a mosaic of radio-receiving elements each having radio-wave receiving antenna means tuned to the frequency of the radio waves and rectifying means responsive to the radio waves received by the antenna means, and a mosaic having elements corresponding, respectively, to the radio-receiying elements and capacitively coupled thereto, one of the mosaics being carried by the screen.

17. An electric system having, in combination, a plurality of permanently charged elements each comprising a permanently polarized dielec5 trie base, means for producing an electron stream for impinging on the plurality of elements, and means for causing the electron stream to scan the plurality of elements.

18. An electric system having, in combination, an oscilloscope-like member having a mosaic of permanently charged elements each comprising a permanently polarized dielectric base adapted to absorb radio waves, means for producing an electron stream for impinging on the mosaic, and means for causing said stream to scan the mosaic.

19. An electric system having, in combination, a plurality of sets of permanently charged elements each comprising a permanently polarized zo dielectric base, the elements of each set being connected together to a common terminal, a load, and means for connecting the common terminals to the load.

20. An electric system having, in combination, .35 a plurality of sets of normally ineffective permanently charged elements each comprising a permanently polarized dielectric base, the elements of each set being connected together to a common terminal, a load, means for connecting the common terminals to the load, and means for rendering the elements of successive sets successively effective.

21. An electric system having, in combination, permanently charged means comprising a permanently polarized dielectric base, and means for producing an electron stream for impinging on the permanently charged means.

22. In combination with a plurality of permanently charged elements each comprising a permanently polarized dielectric base, a plurality of elements corresponding, respectively, to the plurality of permanently charged elements and capacitively coupled thereto.

23. A mosaic having an insulating support, and a plurality of permanently charged elements each comprising a permanently polarized dielectric base supported by the support.

24. An electron tube having a screen, and a mosaic of permanently charged elements each comprising a permanently polarized dielectric base supported by the screen.

25. An electric system having, in combination, a plurality of permanently charged elements comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base, means for producing an electron stream for impinging on the plurality of elements, and means for causing the electron stream to scan the plurality of elements.

26. An electric system having, in combination, an oscilloscope-like member having a mosaic of permanently charged elements each comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base adapted to absorb and rectify radio waves, means for producing an electron stream for impinging on the mosaic, and means for causing said stream to scan the mosaic.

27. An electric system having, in combination, a plurality of sets of permanently charged elements each comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base, the elements of each set being connected together to a common terminal, a load, and means for connecting the common terminals to the load.

28. An electric system having, in combination, a plurality of sets of normally ineffective permanently charged elements each comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base, the elements of each set being connected together to a common terminal, a load, means for connecting the common terminals to the load, and means for rendering the elements of successive sets successively effective.

29. An electric system having, in combination, .permanently charged means comprising a mixture of radio-wave atasorbing-and-rectifying material with a permanently polarized dielectric base, and means for producing an electron stream for impinging on the permanently charged means.

30. In combination with a plurality of permanently charged elements each comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base, a plurality of elements corresponding, respectively, to the plurality of permanently charged elements and capacitively coupled thereto.

31. A mosaic having an insulating support, and a plurality of permanently charged elements each comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base supported by the support.

32. An electron tube having a screen, and a mosaic of permanently charged elements each comprising a mixture of radio-wave absorbing-and-rectifying material with a permanently polarized dielectric base supported by the screen.

ROBERT H. RINES.

LOAD-DATE: November 14, 2005

1029ZH

********** Print Completed **********

Time of Request: Wednesday, August 01, 2007 11:58:25 EST

Print Number: 1821:40503956
Number of Lines: 292
Number of Pages: 8

Send To: NANCHAHAL, NEHA
PIERCE LAW CENTER
2 WHITE ST
CONCORD, NH 03301-4176